



HARBOR

SMART HOMES

Home Automation Made Easy

Smoke & CO Listener



- The front cover design of the alarm may vary but product function remains the same
- This device is certified to work with Ring; Requires Ring Alarm Base Station to Work with Ring. Enjoy improved compatibility, easier setup and a seamless in-app experience. Temperature Range: 40°F (4°C) to 100°F (38°C). Humidity Range: 10% to 95% relative humidity (RH)
- Receive real-time notifications in the Ring App when smoke or carbon monoxide is detected. Do not insert the batteries into your First Alert alarm until prompted by the Ring app
- Certified to work with smart home systems such as Ring Alarm Base Station, Samsung SmartThings, and Nexia Home Intelligence when connected to a Z-Wave Plus gateway hub (sold separately; Not compatible with Wink or Onelink)
- Help keep your family safe with this battery-powered smoke detector and carbon monoxide alarm; includes 2 AA batteries
- The Z-Wave Plus with Smart Start feature allows a faster and more intuitive connection of device to hub and on-boarding via QR code scan located on device
- Photoelectric smoke sensor helps reduce false alarms caused by cooking or shower steam
- Includes an 85-decibel horn, single test/silence button, side access to a tamper-resistant battery door, and pins that lock the alarm to the mounting bracket